

ASUS ROG STRIX B850-G GAMING WIFI AMD B850 Soket AM5 micro ATX

Marka : ASUS

Ürün kodu: 90MB1M30-M0EAY0

Ürün Adı : ROG STRIX B850-G GAMING WIFI

ASUS ROG STRIX B850-G GAMING WIFI. İşlemci üreticisi: AMD, İşlemci soketi: Soket AM5, İşlemcilerle uyumlu: AMD Ryzen 7000 Series, AMD Ryzen 8000 Series, AMD Ryzen 9000 Series. Destekli hafıza türü: DDR5-SDRAM, Maksimum bellek: 256 GB, Hafıza alanı türü: DIMM. Desteklenen depolama sürücüsü arayüzleri: M.2, SATA III, Desteklenen depolama sürücüsü tipleri: HDD & SSD, RAID seviyesi: 0, 1, 5, 10. Ethernet arayüz türü: 2.5 Gigabit Ethernet, Wi-Fi standardı: Wi-Fi 7 (802.11be), Wi-Fi standartları: Wi-Fi 7 (802.11be). Bileşen: PC, Anakart form faktörü: micro ATX, Analevha yonga kümesi ailesi: AMD



5 YIL GARANTİ UZATMA ÜRÜN KAYIT SAYFASI



*Ürününüzü kaydetmek için QR kodu okutunuz.

İşlemci		Ağ Bağlantıları	
İşlemci üreticisi *	AMD	Ethernet LAN bağlantısı	✓
İşlemci soketi *	Soket AM5	Ethernet arayüz türü	2.5 Gigabit Ethernet
İşlemcilerle uyumlu *	AMD Ryzen 7000 Series, AMD Ryzen 8000 Series, AMD Ryzen 9000 Series	Wi-Fi *	✓
		Wi-Fi standardı	Wi-Fi 7 (802.11be)
		Wi-Fi standartları	Wi-Fi 7 (802.11be)
		Bluetooth	✓
		Bluetooth versiyonu	5.4
Hafıza		Özellikler	
Destekli hafıza türü *	DDR5-SDRAM	Anakart yongası *	AMD B850
Bellek yuvalarının sayısı *	4	Ses çıkış kanalı sayısı *	7.1 kanallar
Hafıza alanı türü	DIMM	Ürün rengi	Beyaz
Hafıza kanalları	Çift kanallı	Bileşen *	PC
ECC uyumluluğu	ECC & ECC olmayan	Anakart form faktörü *	micro ATX
Desteklenen bellek saat hızı (maks.)	8000 MHz	Analevha yonga kümesi ailesi *	AMD
Maksimum bellek *	256 GB	Desteklenen Windows çalışma sistemleri	Windows 11
Tamponsuz hafıza	✓		
Depolama yöneticisi		Genişletme yuvaları	
Desteklenen depolama sürücüsü tipleri	HDD & SSD	PCI Express x16 (Gen 5.x) yuvaları	1
Desteklenen depolama sürücüsü arayüzleri *	M.2, SATA III	M.2 (M) yuvalarının sayısı	4
Desteklenen sabit sürücü sayısı	2		
Desteklenen saklama sürücüsü sayısı	6		
RAID desteği	✓		
RAID seviyesi	0, 1, 5, 10		
Grafik		BIOS	
Paralel işleme teknolojisi desteği *	Desteklenmez	BIOS tipi *	UEFI AMI
		BIOS hafıza boyutu	256 Mbit
		Temiz CMOS düğmesi	✓
		Ambalajlama bilgisi	
		Ambalaj genişliği	285 mm

Dahili I/O		Ambalajlama bilgisi	
USB 2.0 bağlayıcıları *	2	Ambalaj derinliği	277 mm
USB 3.2 Gen 1 (3.1 Gen 1) konnektörleri *	1	Ambalaj yüksekliği	72,5 mm
USB 3.2 Gen 2 (3.1 Gen 2) konnektörleri *	1	Ağırlık & boyutlar	
SATA III bağlantı sayısı *	2	Genişlik	244 mm
Ön panel ses bağlayıcısı	✓	Derinlik	244 mm
Ön panel konektörü	✓	Paket içeriği	
ATX güç bağlayıcı (24-pin)	✓	Anten dahil	✓
CPU fan bağlayıcı	✓	Diğer özellikler	
CPU fan konnektörlerinin sayısı	1	Ses çıkışı	Realtek ALC1220P 7.1 Surround Sound High Definition Audio CODEC*
Şasi fanı bağlayıcı sayısı	3		- Impedance sense for front and rear headphone outputs
Şasi giriş bağlayıcı	✓		- Internal audio Amplifier to enhance the highest quality sound for headphone and speakers
EPS güç bağlantısı (8-iğne)	✓		- Supports: Jack-detection, Multi-streaming, Front Panel Jack-retasking
12V güç konnektörü	✓	Ayarlanabilir özellikler	- High quality 120 dB SNR stereo playback output and 113 dB SNR recording input (Line-in)
Arka panel I/O portları			- Supports up to 32-Bit/192 kHz playback*
USB 2.0 bağlantı noktası sayısı *	2		Audio Features
USB 3.2 Gen 1 (3.1 Gen 1) Tip-A port sayısı *	4		- SupremeFX Shielding Technology
USB 3.2 Gen 2 (3.1 Gen 2) Tip-A port sayısı *	2		- Savitech SV3H712 AMP
USB 3.2 Gen 2 (3.1 Gen 2) Tip-C port sayısı *	1		- Rear optical S/PDIF out port
USB 3.2 2x2 C tipi portların sayısı	1		- Premium audio capacitors
Ethernet LAN (RJ-45) port sayısı *	1		- Audio cover
HDMI port sayısı *	1		*A chassis with an HD audio module in the front panel is required to support 7.1 Surround Sound audio output.
DisplayPort	1		Total supports 4 x M.2 slots and 2 x SATA 6Gb/s ports*
Mikrofon giriş fişi	✓		AMD Ryzen™ 9000 & 7000 Series Desktop Processors*
S/PDIF çıkışı	✓	M.2_1 slot (Key M), type 2242/2260/2280 (supports PCIe 4.0 x4 mode)	
WiFi-AP anten soketi	2	M.2_2 slot (Key M), type 2242/2260/2280 (supports PCIe 5.0 x4 mode)	
		AMD Ryzen™ 8000 Series Desktop Processors*	
		M.2_1 slot (Key M), type 2242/2260/2280 (supports PCIe 4.0 x4 mode)	
		M.2_2 slot (Key M), type 2242/2260/2280 (supports PCIe 4.0 x4/x2 mode)	
		AMD B850 Chipset	
		M.2_3 slot (Key M), type 2280 (supports PCIe 4.0 x4)	
		M.2_4 slot (Key M), type 2280 (supports PCIe 4.0 x4) on the underside of the board	
		2 x SATA 6Gb/s ports	
		*Specifications vary by CPU types.	
		4 x DIMM slots, max. 256GB, DDR5	
		Supports up to 8000+MT/s(OC) with Ryzen™ 9000 & 8000 & 7000 Series Processors	
		ECC and Non-ECC Un-buffered DIMM	
		Dual channel memory architecture	
		Supports AMD Extended Profiles for Overclocking (EXPO™)	
		ASUS Enhanced Memory Profile (AEMP)	
		* Supported memory types, data rate (speed), and number of DRAM modules vary depending on the CPU and memory configuration, for more information please refer to CPU/Memory Support list under the Support tab of product information site or visit	
		https://www.asus.com/support/download-center/. Adjustments will be made based on the specifications of mass-produced memory products available on the market.	
		**Non-ECC, un-buffered DDR5 memory supports On-Die ECC function.	
		1 x DisplayPort**	
		1 x HDMI™ port***	
		* Graphics specifications may vary between CPU types. Please refer to AMD CPU specifications.	
		** Supports max. 8K@30Hz as specified in DisplayPort 1.4.	
		*** Supports 4K@60Hz as specified in HDMI 2.1.	
		**** VGA resolution support depends on processors' or graphic cards' resolution.	
		Grafik çıkışı	



4711636092265



0199291092266



199291092266

Catalog Object Cloud



Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity. Automated scraping, data mining, or harvesting for the purpose of training machine learning models, neural networks, or artificial intelligence systems is strictly prohibited without a commercial license.